

# Copy Profiles

This chapter covers the following topics:

- Description
  - Procedure
  - Batch Example
- 

## Description

### Program

B02250

### Function

Copy the profile of a specific cabinet to a group of cabinets.

### Online Input Screen

12:47 PM	* * * C O N - N E C T 3 * * *	14.Feb.94
Cabinet LS	Copy Profiles	B02250
 Replace the selected Cabinet Profiles with Profile from Cabinet _____		
Select all Cabinets starting from Cabinet _____ ending at Cabinet _____ or all Cabinets contained in (SYSCNT) Distribution List _____		
Mark for	<input type="checkbox"/> Command/Object Table <input type="checkbox"/> Cabinet Profile <input type="checkbox"/> Security Levels <input type="checkbox"/> User Profile <input type="checkbox"/> Owners <input type="checkbox"/> Pfkeys	
Enter-PF1---PF2---PF3---PF4---PF5---PF6---PF7---PF8---PF9---PF10--PF11--PF12--- Menu Quit		

## Utility Parameters

Parameter	Format	Description
Cabinet	A8	
Start Cabinet	A8	Either start cabinet or distribution list is required
End Cabinet	A8	Optional
Distribution List	A32	Either distribution list or start cabinet is required
Object/Command Table	A1	Optional
Cabinet Profile	A1	Optional
Security Levels	A1	Optional
User Profile	A1	Optional
Owners	A1	Optional
PFkeys	A1	Optional

## Procedure

The Distribution-list must be defined in cabinet SYSCNT. All cabinets which are members of the list will receive the items marked from the specified cabinet.

The administrator status, overlay calendar ID, language code and mail status message flag of the target cabinets are not modified.

See *Con-nect Administration*, section *Cabinet Maintenance* for information on profiles and security levels.

## Batch Example

All cabinet members of the SYSCNT distribution list DLIST will receive the object/command table, and the cabinet profile of the source-cabinet. This would be coded as follows:

```
LOGON SYSCNT2B
MENU
B02250 sourcecab,,DLIST,X,X
FIN
```